

# 15V 1A Power Supply and PoE Injector with LEDs

## EZ-BP1515

The new **EZ-BP1515** Power Supply and PoE Injector with LEDs is made from TPEE material in an aesthetic package and is available with two RJ45 ports to act as “Data-In” and “PoE+Data out”.

The new **EZ-BP1515** indoor PoE Injector allows you to use your space efficiently when installing your wireless equipment through the smart wall mount case.

The two PoE LED/ Red and ETH LED/Green allows fast and easy control of your equipment.



### Features :

- Fast and easy wall mount case.
- All-In-One Power Supply and POE Injector Included.

### TECHNICAL SPECIFICATIONS

Input Condition	AC100~240V 50/60Hz 0.6A max
Input Rated Voltage	100Vac~200Vac
Input Voltage Rate	90Vac~264Vac
Input Rated Frequency	50/60Hz
Input Frequency Range	47Hz~63Hz
Input Current	0.6A Max
Input Inrush Current	30A Max
Input No Load Power Consumption	0.5 Watt Max @ 115Vac/230Vac
Efficiency	80% Min
Rated Output Voltage & Current	15V/1A
Output Line Regulation	+1%
Output Load Regulation	+5%
Output Over Shoot	10% Max
Output Ripple and Noise	1% Max
Output Rising Time	20ms Max @ 115Vac
Output Hold-Up Time	8ms Min @ 230Vac
Protection	OCP OVP SCP OPP
Dielectric Withstand Voltage	3KV 5mA 60s
Leakage Current	0.25mA @ 230Vac
DC Plug Specification	5.5x2.1x11mm
Dimension	89x70x32mm
Weight	146 gr (Without AC cable)
Operating Temperature Range	0°C~40°C
Storage Temperature Range	-20°C~+85°C
AC Cable	Choice of EU or UK AC Cable
Certifications	CE / UL / GS / RoHS / EMC
Origin	China

### Additional Images



# 15V 1A Power Supply and PoE Injector with LEDs

## EZ-BP1515

### Dimensions

